



Technical Information JX5600

Flash period monitoring :	
Flash interval monitoring :	0,5 s, 1 s, 1.5 s or 2 s
Preventive maintenance :	Individual Flash counter on each installed lamp.
Brilliance selection :	100% (day mode), 10% (crepuscular mode), 3% (night mode)
Brilliance selector :	Digital command via RS485 lan Short circuit on simple systems.
Alarm reporting :	via RS485 digital info. The treatment of these informations is sent to intranet and to port 5556 for a dedicated automat.
Working voltage :	
Consumption :	230 V AC 50/60 Hz +/- 10% (110V AC 60 Hz on demand) less than 100 W
Ambiant temperature rating :	0 °C to + 55 °C Standard 19 " 1U cabinet
Weight :	2 kg